



Slides 18th CMCIM 2024, Toward an algebraic multigrid method for the indefinite Helmholtz equation

Rob Falgout, Matthieu Lecouvez, Pierre Ramet, Clément Richefort

► To cite this version:

Rob Falgout, Matthieu Lecouvez, Pierre Ramet, Clément Richefort. Slides 18th CMCIM 2024, Toward an algebraic multigrid method for the indefinite Helmholtz equation. 18th Copper Mountain Conference On Iterative Methods, Apr 2024, Frisco (Co), United States. cea-04620993


HAL Id: cea-04620993

<https://cea.hal.science/cea-04620993v1>

Submitted on 22 Jun 2024

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.



Toward an AMG method for the indefinite Helmholtz equation

18th Copper Mountain Conference on Iterative Methods - 04/16/24

Rob Falgout¹, (falgout2@llnl.gov)

Matthieu Lecouvez², (matthieu.lecouvez@cea.fr)

Pierre Ramet³, (pierre.ramet@inria.fr)

Clément Richefort², (clement.richefort@cea.fr)

¹LLNL, ²CEA, ³INRIA



Table of contents


- I. Introduction and context on multigrid methods
 - I.1 - Context
 - I.2 - Fundamentals on AMG
 - I.3 - Multigrid for Laplace vs Helmholtz
- II. Smoother for both positive and negative eigenvalues
- III. Interpolation rules for oscillatory near-kernel space
- IV. Alternative coarse correction for indefinite problems
- V. Conclusion




I.1 - Context

- Computation of the **Radar Cross Section** of **3D objects** covered by multiple layers of materials
- Requires **highly accurate** solution of **harmonic Maxwell's equations** in an unbounded domain
- Objects may be electrically **large** + Materials may have **large** permittivity/permeability

⇒ Requires to solve **large** and **sparse** linear systems of equations $Ax = b$



The current **domain decomposition method** is difficult to scale :



- Increase in the **number** of sub-domains
 - ⇒ Convergence is **slower**
- Increase in the **size** of the sub-domains
 - ⇒ Increase in computational **complexity**

We need to investigate an alternative method : **multigrid methods**.



I.2 - Fundamentals on AMG

Multigrid benefits from both **direct** and **iterative** methods :

- ν iterations of a smoother M damp the large eigenvectors.
- The remaining small eigenvectors are projected onto a coarse space defined by P .



Accordingly, the two-grid error propagation matrix is

$$E_{TG} := \underbrace{\left(I - M^{-1}A \right)^\nu}_{\text{Smoker}} \cdot \underbrace{\left(I - P \left(P^T A P \right)^{-1} P^T A \right)}_{\text{Coarse Correction}} \cdot \underbrace{\left(I - M^{-1}A \right)^\nu}_{\text{Smoker}}$$



I.3 - Multigrid applied to Laplace

$$(\text{Laplace Problem}) \Leftrightarrow \begin{cases} -\Delta u = f \text{ on } \Omega = [0, 1] \\ u|_{\partial\Omega} = 0 \end{cases}$$





- Eigenvalues are **positives** → Usual smoothers are perfectly appropriate
- The Near Kernel Space is **smooth** → Convenient assumption for building interpolation
- The matrix A is **s.p.d.** $\Rightarrow \mathbf{x}_{\text{opt}} = P(P^T AP)^{-1}P^T A \mathbf{x} = \arg \min_{\tilde{\mathbf{x}} \in \text{Range}(P)} \|\mathbf{x} - \tilde{\mathbf{x}}\|_A$



I.3 - Multigrid applied to Helmholtz

$$(\text{Helmholtz Problem}) \Leftrightarrow \begin{cases} -\Delta u - k^2 u = f \text{ on } \Omega = [0, 1] \\ u|_{\partial\Omega} = 0 \end{cases}$$



- Eigenvalues are both **positives** and **negatives** → Necessary to find an adapted smoother
- The Near Kernel Space is **oscillatory** → Interpolation rules are difficult to design
- The matrix A is **not s.p.d.** $\Rightarrow \mathbf{x}_{\text{opt}} = P(P^T AP)^{-1}P^T Ax \neq \arg \min_{\tilde{\mathbf{x}} \in \text{Range}(P)} \|\mathbf{x} - \tilde{\mathbf{x}}\|_A$ not a norm



Table of contents

- I. Introduction and context on multigrid methods
- **II. Smoother for both positive and negative eigenvalues**
- III. Interpolation rules for oscillatory near-kernel space
- IV. Alternative coarse correction for indefinite problems
- V. Conclusion



II. Smoother for both positive and negative eigenvalues

In the indefinite case, large eigenvalues can be either **positive** or **negative**

→ *Chebyshev Polynomial Smoother* built on *normal equations* will be considered




Figure 1: Spectrum of $q(A^2) := I - p(A^2)A^2$



Table of contents

- I. Introduction and context on multigrid methods
- II. Smoother for both positive and negative eigenvalues
- III. Interpolation rules for oscillatory near-kernel space
 - III.1 - Theory for SPD matrices
 - III.2 - Construction of interpolation rules for oscillatory problems
- IV. Alternative coarse correction for indefinite problems
- V. Conclusion



III.1 - Theory for SPD matrices

Let A and M be SPD matrices. The theory¹ provides the definition of the ideal interpolation operator

$$P_* := \left(I - S \left(S^T A S \right)^{-1} S^T A \right) R^T,$$

based on orthogonal coarse / fine variables selection operators R / S^T ($RS = 0$). In particular,

$$\mu_M(P_*, \mathbf{e}) = \min_P \max_{\mathbf{e} \neq 0} \mu_M(P, \mathbf{e}), \text{ with } \mu_M(P, \mathbf{e}) = \frac{\|(I - PR)\mathbf{e}\|_M^2}{\|\mathbf{e}\|_A^2}.$$

The optimal theory² provides the optimal interpolation operator $P_\#$ such that

$$\text{Range}(P_\#) = \text{span}(\{\mathbf{w}_1, \dots, \mathbf{w}_{n_c}\}), \text{ with } A\mathbf{w}_i = \sigma_i M\mathbf{w}_i \text{ and } \sigma_i \leq \sigma_{i+1}.$$

Ideal and optimal theories can coincide for a particular choice of $R_\#$ and $S_\#$ so that

$$P_\# = P_* = \left(I - S_\# \left(S_\#^T A S_\# \right)^{-1} S_\#^T A \right) R_\#^T \quad (1)$$

¹ On Generalizing the AMG Framework - Robert D. Falgout and Panayot S. Vassilevski (2003)

² Optimal Interpolation and Compatible Relaxation in Classical Algebraic Multigrid - Brannick et al. (2018)



III.2 - Interpolation rules for oscillatory problems

- 1 Define T_κ the set of κ test vectors such that

$$T_\kappa := \begin{bmatrix} q_m(A) \mathbf{p}_1 & \cdots & q_m(A) \mathbf{p}_\kappa \end{bmatrix}, \text{ with } \mathbf{p}_i := \text{random vector } (n)$$



III.3 - Interpolation rules for oscillatory problems

- 1 Define T_κ the set of κ test vectors such that

$$T_\kappa := \begin{bmatrix} | & & | \\ q_m(A)\mathbf{p}_1 & \cdots & q_m(A)\mathbf{p}_\kappa \\ | & & | \end{bmatrix}, \text{ with } \mathbf{p}_i := \text{random vector } (n)$$

- 2 Let coarse and non-coarse variables selection operators respectively be

$$\hat{\mathbf{R}}^T = [R_f \ I_c]^T, \ \hat{\mathbf{S}} = [I_f \ -R_f^T]^T, \ RS = 0$$

where each row sparse row of r_i is defined as follows

$$\forall i \in \mathcal{F}, \ \mathbf{r}_i = \arg \min_{\mathbf{r}} \sum_{j=1}^{\kappa} (T_{i,j} - \mathbf{r} \cdot T_{C_i,j})^2 \ (\mathbf{r}_i \text{ row of } R_f)$$



III.3 - Interpolation rules for oscillatory problems

- 1 Define T_κ the set of κ test vectors such that

$$T_\kappa := \begin{bmatrix} q_m(A) \mathbf{p}_1 & \cdots & q_m(A) \mathbf{p}_\kappa \end{bmatrix}, \text{ with } \mathbf{p}_i := \text{random vector } (n)$$

- 2 Let coarse and non-coarse variables selection operators respectively be

$$\hat{\mathbf{R}}^T = [R_f \ I_c]^T, \quad \hat{\mathbf{S}} = [I_f \ -R_f^T]^T, \quad RS = 0$$

where each row sparse row of r_i is defined as follows

$$\forall i \in \mathcal{F}, \quad \mathbf{r}_i = \arg \min_{\mathbf{r}} \sum_{j=1}^{\kappa} (T_{i,j} - \mathbf{r} \cdot T_{C_i,j})^2 \quad (\mathbf{r}_i \text{ row of } R_f)$$

- 3 Approximate the ideal interpolation operator column-wise by

$$\hat{P}_{:,i} := (I - S X_i^T (X_i S^T A^T A S X_i^T)^{-1} X_i S^T A^T A) \hat{\mathbf{R}}_{:,i}^T.$$

where X_i corresponds to a non-zero pattern constraint matrix for the i^{th} column of \hat{P} .



Table of contents

- I. Introduction and context on multigrid methods
- II. Smoother for both positive and negative eigenvalues
- III. Interpolation rules for oscillatory near-kernel space
- IV. Alternative coarse correction for indefinite problems
 - IV.1 - The problem of the classical coarse correction
 - IV.2 - Alternative coarse correction
- V. Conclusion




IV.1 - The problem of the classical coarse correction

We illustrate the problem of the coarse correction with a shifted 2D Laplacian problem :

$$(L_n - \alpha I_n) \mathbf{x} = \mathbf{b}, \text{ with } n = 100$$

We plot three curves which correspond to

- \mathbf{v}_1 - The smallest eigenvector of the matrix $(L_n - \alpha I_n)$
- $P(P^T P)^{-1} P^T \mathbf{v}_1$ - The L^2 -projection of \mathbf{v}_1 onto Range(P)
- $P(P^T A P)^{-1} A \mathbf{v}_1$ - The coarse correction applied to \mathbf{v}_1






IV.1 - The problem of the classical coarse correction

We illustrate the problem of the coarse correction with a shifted 2D Laplacian problem :

$$(L_n - 0.625^2 I_n) \mathbf{x} = \mathbf{b}, \text{ with } n = 100$$

We plot three curves which correspond to

- \mathbf{v}_1 - The smallest eigenvector of the matrix $(L_n - 0.625^2 I_n)$
- $P(P^T P)^{-1} P^T \mathbf{v}_1$ - The L^2 -projection of \mathbf{v}_1 onto Range(P)
- $P(P^T A P)^{-1} A \mathbf{v}_1$ - The coarse correction applied to \mathbf{v}_1






IV.1 - The problem of the classical coarse correction

We illustrate the problem of the coarse correction with a shifted 2D Laplacian problem :

$$(L_n - 1.435^2 I_n) \mathbf{x} = \mathbf{b}, \text{ with } n = 100$$

We plot three curves which correspond to

- \mathbf{v}_1 - The smallest eigenvector of the matrix $(L_n - 1.435^2 I_n)$
- $P(P^T P)^{-1} P^T \mathbf{v}_1$ - The L^2 -projection of \mathbf{v}_1 onto Range(P)
- $P(P^T A P)^{-1} A \mathbf{v}_1$ - The coarse correction applied to \mathbf{v}_1






IV.1 - The problem of the classical coarse correction

We illustrate the problem of the coarse correction with a simple model problem :

$$(L_n - 1.710^2 I_n) \mathbf{x} = \mathbf{b}, \text{ with } n = 100$$

We plot three curves which correspond to

- \mathbf{v}_1 - The smallest eigenvector of the matrix $(L_n - 1.710^2 I_n)$
- $P(P^T P)^{-1} P^T \mathbf{v}_1$ - The L^2 -projection of \mathbf{v}_1 onto Range(P)
- $P(P^T A P)^{-1} A \mathbf{v}_1$ - The coarse correction applied to \mathbf{v}_1





IV.1 - The problem of the classical coarse correction

Let P be a $n \times 1$ interpolation operator whose range approximates a small eigenvector \mathbf{v}_1 as follows

$$\text{Range}(P) = \left\{ \mathbf{v}_1 + \sum_{j>1} \epsilon_j \mathbf{v}_j \right\}.$$



IV.1 - The problem of the classical coarse correction

Let P be a $n \times 1$ interpolation operator whose range approximates a small eigenvector \mathbf{v}_1 as follows

$$\text{Range}(P) = \left\{ \mathbf{v}_1 + \sum_{j>1} \epsilon_j \mathbf{v}_j \right\}.$$

Define \mathbf{p}_1 the “eigenvector pollution” of \mathbf{v}_1 such that

$$\mathbf{p}_1 := \mathbf{v}_1 - P(P^T P)^{-1} P^T \mathbf{v}_1 = - \sum_{j>1} \epsilon_j \mathbf{v}_j.$$



IV.1 - The problem of the classical coarse correction

Let P be a $n \times 1$ interpolation operator whose range approximates a small eigenvector \mathbf{v}_1 as follows

$$\text{Range}(P) = \left\{ \mathbf{v}_1 + \sum_{j>1} \epsilon_j \mathbf{v}_j \right\}.$$

Define \mathbf{p}_1 the “eigenvector pollution” of \mathbf{v}_1 such that

$$\mathbf{p}_1 := \mathbf{v}_1 - P(P^T P)^{-1} P^T \mathbf{v}_1 = - \sum_{j>1} \epsilon_j \mathbf{v}_j.$$

This eigenvector pollution produces an “eigenvalue pollution” δ_1 so the damping factor of \mathbf{v}_1 is

$$\mathbf{v}_1^T E \mathbf{v}_1 = 1 - \frac{\lambda_1}{\lambda_1 + \delta_1} \text{ with } \delta_1 := \sum_{j>1} \epsilon_j^2 \lambda_j \geq 0.$$



IV.1 - The problem of the classical coarse correction

Let P be a $n \times 1$ interpolation operator whose range approximates a small eigenvector \mathbf{v}_1 as follows

$$\text{Range}(P) = \left\{ \mathbf{v}_1 + \sum_{j>1} \epsilon_j \mathbf{v}_j \right\}.$$

Define \mathbf{p}_1 the “eigenvector pollution” of \mathbf{v}_1 such that

$$\mathbf{p}_1 := \mathbf{v}_1 - P(P^T P)^{-1} P^T \mathbf{v}_1 = - \sum_{j>1} \epsilon_j \mathbf{v}_j.$$

This eigenvector pollution produces an “eigenvalue pollution” δ_1 so the damping factor of \mathbf{v}_1 is

$$\mathbf{v}_1^T E \mathbf{v}_1 = 1 - \frac{\lambda_1}{\lambda_1 + \delta_1} \text{ with } \delta_1 := \sum_{j>1} \epsilon_j^2 \lambda_j \geq 0.$$

A.s.p.d : $\delta_1 \geq 0 \Rightarrow 0 < \mathbf{v}_1^T E \mathbf{v}_1 < 1$ The coarse correction never amplifies the error



IV.1 - The problem of the classical coarse correction

Let P be a $n \times 1$ interpolation operator whose range approximates a small eigenvector \mathbf{v}_1 as follows

$$\text{Range}(P) = \left\{ \mathbf{v}_1 + \sum_{j>1} \epsilon_j \mathbf{v}_j \right\}.$$

Define \mathbf{p}_1 the “eigenvector pollution” of \mathbf{v}_1 such that

$$\mathbf{p}_1 := \mathbf{v}_1 - P(P^T P)^{-1} P^T \mathbf{v}_1 = - \sum_{j>1} \epsilon_j \mathbf{v}_j.$$

This eigenvector pollution produces an “eigenvalue pollution” δ_1 so the damping factor of \mathbf{v}_1 is


$$\mathbf{v}_1^T E \mathbf{v}_1 = 1 - \frac{\lambda_1}{\lambda_1 + \delta_1} \text{ with } \delta_1 := \sum_{j>1} \epsilon_j^2 \lambda_j.$$

A indefinite : $-1 < \mathbf{v}_1^T E \mathbf{v}_1 < 1 \Rightarrow \delta_1 \geq -\frac{1}{2}\lambda_1 \Rightarrow$ The coarse correction may amplify the error



IV.2 - Alternative coarse correction

The shape of the **coarse correction vector** is correct when p_i is small, only the direction is wrong



Hence, coarse correction vectors still provide information on the near-kernel space!



IV.2 - Alternative coarse correction

For each multigrid cycle m :

- 1 Create the coarse correction subspace

$$W_m = \left[P(P^T AP)^{-1} P^T A \mathbf{r}^{(0)}, \dots, P(P^T AP)^{-1} P^T A \mathbf{r}^{(m)} \right]$$



IV.2 - Alternative coarse correction

For each multigrid cycle m :

- 1 Create the coarse correction subspace

$$W_m = \left[P(P^T AP)^{-1} P^T A \mathbf{r}^{(0)}, \dots, P(P^T AP)^{-1} P^T A \mathbf{r}^{(m)} \right]$$

- 2 Construct the operators involved in the below generalized Arnoldi relation

$$A W_m = Z_m H_m,$$

where $\text{Range}(Z_m) = \text{span}\{A\mathbf{w}_1, \dots, A\mathbf{w}_m\}$ and H_m is an $m \times m$ Hessenberg matrix.



IV.2 - Alternative coarse correction

For each multigrid cycle m :

- 1 Create the coarse correction subspace

$$W_m = \left[P(P^T AP)^{-1} P^T A \mathbf{r}^{(0)}, \dots, P(P^T AP)^{-1} P^T A \mathbf{r}^{(m)} \right]$$

- 2 Construct the operators involved in the below generalized Arnoldi relation

$$A W_m = Z_m H_m,$$

where $\text{Range}(Z_m) = \text{span}\{A\mathbf{w}_1, \dots, A\mathbf{w}_m\}$ and H_m is an $m \times m$ Hessenberg matrix.

- 3 Approximate the solution in the coarse correction subspace in a proper-norm

$$x_* = \arg \min_{\tilde{x} \in \text{Range}(W_m)} \| \mathbf{b} - A \tilde{x} \|_2 = W_m H_m^{-1} Z_m^T \mathbf{b}$$



IV.2 - Alternative coarse correction

For each multigrid cycle m :

- 1 Create the coarse correction subspace

$$W_m = \left[P(P^T AP)^{-1} P^T A \mathbf{r}^{(0)}, \dots, P(P^T AP)^{-1} P^T A \mathbf{r}^{(m)} \right]$$

- 2 Construct the operators involved in the below generalized Arnoldi relation

$$AW_m = Z_m H_m,$$

where $\text{Range}(Z_m) = \text{span}\{A\mathbf{w}_1, \dots, A\mathbf{w}_m\}$ and H_m is an $m \times m$ Hessenberg matrix.

- 3 Approximate the solution in the coarse correction subspace in a proper-norm

$$x_* = \underset{\tilde{x} \in \text{Range}(W_m)}{\arg \min} \| \mathbf{b} - A\tilde{x} \|_2 = W_m H_m^{-1} Z_m^T \mathbf{b}$$


Downside of euclidean minimization : Eigenvalues are squared

$$\Rightarrow \mathbf{v}_1^T E_{W_m} \mathbf{v}_1 = 1 - \frac{\lambda_1^2}{\lambda_1^2 + \delta_1} \text{ with } \delta_1 := \sum_{j>1} \epsilon_j^2 \lambda_j^2.$$



IV.2 - Alternative coarse correction

Approximation of the smallest eigenvector \mathbf{v}_1 after 1 cycle - $(L_n - 0.625^2 I_n)$



$$\text{Range}(W_1) = \text{span} \left(\left\{ P(P^T AP)^{-1}P^T A \mathbf{v}_1 \right\} \right)$$



IV.2 - Alternative coarse correction

For each multigrid cycle m :

- 1 Create the coarse correction subspace

$$W_m = \left[P(P^T AP)^{-1} P^T A \mathbf{r}^{(0)}, \dots, P(P^T AP)^{-1} P^T A \mathbf{r}^{(m)} \right]$$

- 2 Construct the operators involved in the below generalized Arnoldi relation

$$AW_m = Z_m H_m,$$

where $\text{Range}(Z_m) = \text{span}\{A\mathbf{w}_1, \dots, A\mathbf{w}_m\}$ and H_m is an $m \times m$ Hessenberg matrix.

- 3 Approximate the solution in the coarse correction subspace in a proper-norm

$$x_* = \underset{\tilde{x} \in \text{Range}(W_m)}{\arg \min} \| \mathbf{b} - A\tilde{x} \|_2 = W_m H_m^{-1} Z_m^T \mathbf{b}$$

Downside of euclidean minimization : Eigenvalues are squared

$$\Rightarrow \mathbf{v}_1^T E_{W_m} \mathbf{v}_1 = 1 - \frac{\lambda_1^2}{\lambda_1^2 + \delta_1} \text{ with } \delta_1 := \sum_{j>1} \epsilon_j^2 \lambda_j^2.$$



IV.2 - Alternative coarse correction

For each multigrid cycle m :

- 1 Create the **smoothed** coarse correction subspace

$$W_m = \left[q(A)^\nu P(P^T AP)^{-1} P^T A r^{(0)}, \dots, q(A)^\nu P(P^T AP)^{-1} P^T A r^{(m)} \right]$$

- 2 Construct the operators involved in the below generalized Arnoldi relation

$$AW_m = Z_m H_m,$$

where $\text{Range}(Z_m) = \text{span}\{Aw_1, \dots, Aw_m\}$ and H_m is an $m \times m$ Hessenberg matrix.

- 3 Approximate the solution in the **smoothed** coarse correction subspace in a proper-norm

$$x_* = \arg \min_{\tilde{x} \in \text{Range}(W_m)} \|b - Ax\|_2 = W_m H_m^{-1} Z_m^T b$$


Downside of euclidean minimization : Eigenvalues are squared

$$\Rightarrow v_1^T E_{W_m} v_1 = 1 - \frac{\lambda_1^2}{\lambda_1^2 + \delta_1} \text{ with } \delta_1 := \sum_{j>1} \left(\frac{q(\lambda_j^2)}{q(\lambda_1^2)} \right)^\nu \epsilon_j^2 \lambda_j^2.$$



IV.2 - Alternative coarse correction

Approximation of the smallest eigenvector v_1 after 1 cycle - $(L_n - 0.625^2 I_n)$




$$\text{Range}(W_1) = \text{span} \left(\left\{ q(A) P(P^T AP)^{-1} P^T A v_1 \right\} \right)$$



IV.2 - Alternative coarse correction

Approximation of the smallest eigenvector v_1 after 1 cycle - $(L_n - 0.625^2 I_n)$




$$\text{Range}(W_1) = \text{span} \left(\left\{ q(A)^2 P(P^T AP)^{-1} P^T A v_1 \right\} \right)$$



IV.2 - Alternative coarse correction

Approximation of the smallest eigenvector v_1 after 2 cycles - $(L_n - 0.625^2 I_n)$




$$\text{Range}(W_2) = \text{span} \left(\left\{ q(A)^2 P(P^T AP)^{-1} P^T A v_1, q(A)^2 P(P^T AP)^{-1} P^T A \cdot E_{TG} v_1 \right\} \right)$$



IV.2 - Alternative coarse correction


Approximation of the smallest eigenvector v_1 after 5 cycles - $(L_n - 0.625^2 I_n)$



$$\text{Range}(W_5) = \text{span} \left(\left\{ q(A)^2 P(P^T AP)^{-1} P^T A v_1, \dots, q(A)^2 P(P^T AP)^{-1} P^T A \cdot (E_{TG})^4 v_1 \right\} \right)$$

IV.2 - Alternative coarse correction

Approximation of the smallest eigenvector v_1 after 1 cycle - $(L_n - 1.435^2 I_n)$




$$\text{Range}(W_1) = \text{span} \left(\left\{ q(A)^2 P(P^T AP)^{-1} P^T A v_1 \right\} \right)$$



IV.2 - Alternative coarse correction

Approximation of the smallest eigenvector v_1 after 2 cycles - $(L_n - 1.435^2 I_n)$




$$\text{Range}(W_2) = \text{span} \left(\left\{ q(A)^2 P(P^T AP)^{-1} P^T A v_1, q(A)^2 P(P^T AP)^{-1} P^T A \cdot E_{TG} v_1 \right\} \right)$$



IV.2 - Alternative coarse correction

Approximation of the smallest eigenvector v_1 after 5 cycles - $(L_n - 1.435^2 I_n)$




$$\text{Range}(W_5) = \text{span} \left(\left\{ q(A)^2 P(P^T AP)^{-1} P^T A v_1, \dots, q(A)^2 P(P^T AP)^{-1} P^T A \cdot (E_{TG})^4 v_1 \right\} \right)$$



IV.2 - Alternative coarse correction

Approximation of the smallest eigenvector v_1 after 1 cycle - $(L_n - 1.713^2 I_n)$




$$\text{Range}(W_1) = \text{span} \left(\left\{ q(A)^2 P(P^T AP)^{-1} P^T A v_1 \right\} \right)$$



IV.2 - Alternative coarse correction

Approximation of the smallest eigenvector v_1 after 2 cycles - $(L_n - 1.713^2 I_n)$




$$\text{Range}(W_2) = \text{span} \left(\left\{ q(A)^2 P(P^T AP)^{-1} P^T A v_1, q(A)^2 P(P^T AP)^{-1} P^T A \cdot E_{TG} v_1 \right\} \right)$$



IV.2 - Alternative coarse correction

Approximation of the smallest eigenvector v_1 after 5 cycles - $(L_n - 1.713^2 I_n)$



$$\text{Range}(W_5) = \text{span} \left(\left\{ q(A)^2 P(P^T A P)^{-1} P^T A v_1, \dots, q(A)^2 P(P^T A P)^{-1} P^T A \cdot (E_{TG})^4 v_1 \right\} \right)$$



Table of contents

- I. Introduction and context on multigrid methods
- II. Smoother for both positive and negative eigenvalues
- III. Interpolation rules for oscillatory near-kernel space
- IV. Alternative coarse correction for indefinite problems
- V. Conclusion



V. Conclusion


With no assumption on the underlying geometry, we designed :

- 1 A smoother for indefinite problems that damps the desired proportion of eigenvalues.
- 2 Interpolation rules that propagates the oscillatory smallest eigenvectors.
- 3 An alternative coarse correction based on Krylov outer iterations.

Topics of further research :

- 1 Enable Chebyshev nodes for disjoint intervals to avoid normal equations.
- 2 The sparsity of the interpolation operator has to be improved drastically.
- 3 Reduce the number of SpMv.

A paper is in progress...



Thanks! Any questions?



Appendix - Numerical Experiment

2D Helmholtz problem with absorbing boundary conditions, discretized with 10 points / wavelength (i.e., $kh = 0.625$).

- Number of smoothing steps $\nu := 2$.
- Number of test vectors $\kappa := 30$.
- Max number of interpolation points in the LSM set-up phase is 4.
- Multigrid stops when the relative residual norm becomes lower than 10^{-6} .




Figure 2: Number of iterations following the wavenumber k



Appendix - Numerical Experiment




Figure 3: Number of iterations following the wavenumber k

Appendix - Numerical Experiment




Figure 4: Operators complexity following the wavenumber k - $\phi := \frac{\sum_I \text{nnz}(A_I)}{\text{nnz}(A_0)}$