



**HAL**  
open science

## Electromagnetic validation of an end-to-end communication model for reconfigurable intelligent surfaces based on mutual impedances

Sergio Terranova, Samara Gharbieh, Moufida Bouslama, Antonio Clemente, Raffaele d'Errico, Jean Baptiste Gros, Geoffroy Lerosey, Marco Di Renzo, Gabriele Gradoni

### ► To cite this version:

Sergio Terranova, Samara Gharbieh, Moufida Bouslama, Antonio Clemente, Raffaele d'Errico, et al.. Electromagnetic validation of an end-to-end communication model for reconfigurable intelligent surfaces based on mutual impedances. URSI AT-AP-RASC 2022 - 3rd URSI Atlantic Radio Science Meeting, May 2022, La Grande Canarie, Spain. cea-04372139

**HAL Id: cea-04372139**

**<https://cea.hal.science/cea-04372139v1>**

Submitted on 4 Jan 2024

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.



## Electromagnetic Validation of an End-to-End Communication Model for Reconfigurable Intelligent Surfaces based on Mutual Impedances

Sergio Terranova<sup>\*(1)</sup>, Samara Gharbieh<sup>(2)</sup>, Moufida Bouslama<sup>(2)</sup>, Antonio Clemente<sup>(2)</sup>, Raffaele D'Errico<sup>(2)</sup>, Jean Baptiste Gros<sup>(3)</sup>, Geoffroy Lerosey<sup>(3)</sup>, Marco Di Renzo<sup>(4)</sup>, and Gabriele Gradoni<sup>(1)</sup>

(1) School of Mathematical Sciences, University of Nottingham, United Kingdom  
(e-mail: sergio.terranova@nottingham.ac.uk, gabriele.gradoni@nottingham.ac.uk)

(2) CEA-Leti, Grenoble, France

(e-mail: samara.gharbieh@cea.fr, moufida.bouslama@cea.fr, antonio.clemente@cea.fr, raffaele.derrico@cea.fr)

(3) Greenerwave, Paris, France

(e-mail: jean-baptiste.gros@greenerwave.com, geoffroy.lerosey@greenerwave.com)

(4) Université Paris-Saclay, CNRS, CentraleSupélec, Laboratoire des Signaux et Systèmes, France

(e-mail: marco.di-renzo@universite-paris-saclay.fr)

Reconfigurable Intelligent Surfaces (RISs) constitute a promising new technology for controlling and managing the wireless propagation channel, enabling the idea of the wireless environment as a service [1]. RISs are large electronically-controlled electromagnetic metasurfaces (MS) comprising a huge number of low-cost passive sub-wavelength reflecting elements, referred to as unit cells. By properly tuning the reflection phase and amplitude of these individual elements, one can engineer the desired electromagnetic (EM) properties of the reflected wavefront to obtain specific EM functionalities, e.g., beam steering, focusing, interference mitigation, coverage extension, and more [2], [3]. Modelling the electromagnetic propagation of signals in such RIS-enabled environments has therefore become a point of crucial importance in future beyond 5G/6G architectures, and faces significant EM modelling challenges [3]. In [4] the authors introduced an electromagnetic compliant communication model for the end-to-end RIS-assisted wireless channel, based on an impedance matrix formalism. This model has been verified for minimum scattering linear antennas and there is now need to validate the mathematical structure in the far-field with real-life prototypes. In this work, a procedure to validate the proposed model is presented that relies on the extraction of impedance matrices from commercial full-wave EM software. In particular, two RISs based on different unit-cell designs, operating at 5 GHz and 29 GHz respectively, were tested. The first structure is the design of a 2×2 unit cells RIS (2 ports on each unit cells) operating at 5 GHz. This unit cell, designed by Greenerwave [5], uses a p-i-n diodes to control a binary reflection phase on both the vertical and the horizontal polarizations. The second structure is a 2×2 RIS designed at CEA Leti [6], which operates at 29 GHz. In this case, two p-i-n diodes are used to implement a binary phase control on a single linear polarization. For both configurations, a very good agreement has been found between model predictions from the end-to-end formulation and the analysis conducted via full-wave simulations. Achieved results pave the way to the integration of EM models within optimization algorithms adopted in wireless communication networks.

- [1] E. C. Strinati *et al.*, “Wireless Environment as a Service Enabled by Reconfigurable Intelligent Surfaces: The RISE-6G Perspective,” in *2021 Joint European Conference on Networks and Communications 6G Summit (EuCNC/6G Summit)*, Jun. 2021, pp. 562–567. doi: 10.1109/EuCNC/6GSummit51104.2021.9482474.
- [2] M. D. Renzo *et al.*, “Smart radio environments empowered by reconfigurable AI meta-surfaces: an idea whose time has come,” *EURASIP J. Wirel. Commun. Netw.*, vol. 2019, no. 1, p. 129, Dec. 2019, doi: 10.1186/s13638-019-1438-9.
- [3] M. Di Renzo *et al.*, “Smart Radio Environments Empowered by Reconfigurable Intelligent Surfaces: How It Works, State of Research, and The Road Ahead,” *IEEE J. Sel. Areas Commun.*, vol. 38, no. 11, pp. 2450–2525, Nov. 2020, doi: 10.1109/JSAC.2020.3007211.
- [4] G. Gradoni and M. Di Renzo, “End-to-End Mutual Coupling Aware Communication Model for Reconfigurable Intelligent Surfaces: An Electromagnetic-Compliant Approach Based on Mutual Impedances,” *IEEE Wirel. Commun. Lett.*, vol. 10, no. 5, pp. 938–942, May 2021, doi: 10.1109/LWC.2021.3050826.
- [5] “Greenerwave - We shape electromagnetic waves,” *Greenerwave*. <https://greenerwave.com/> (accessed Jan. 20, 2022).
- [6] CEA, “Welcome,” *CEA/Leti (english)*, Oct. 19, 2013. <https://www.cea.fr/cea-tech/leti/english/Pages/Welcome.aspx> (accessed Jan. 20, 2022).