



HAL
open science

Development of a standardless miniature XRF system for the analysis of actinides: coupling MC modelling and fundamental parameters

Tetiana Sokoltsova, Marie-Christine Lepy, Eric Esbelin

► To cite this version:

Tetiana Sokoltsova, Marie-Christine Lepy, Eric Esbelin. Development of a standardless miniature XRF system for the analysis of actinides: coupling MC modelling and fundamental parameters. 19^{èmes} Journées Scientifiques de Marcoule, Sep 2019, Bagnols-sur-Ceze, France. cea-04741151

HAL Id: cea-04741151

<https://cea.hal.science/cea-04741151v1>

Submitted on 17 Oct 2024

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Development of a standardless miniature XRF system for the analysis of actinides: coupling MC modelling and fundamental parameters

Nom, Prénom : Sokoltsova Tetiana
Responsable CEA : Esbelin Eric
Directeur universitaire : Lepy Marie-Christine
Laboratoire d'accueil : DMRC/SA21/L2AT
Date de début de thèse : 28/11/2017

Contrat : CTBU
Organisme co-financier :
Université d'inscription : Université Paris-Saclay
Ecole doctorale : PHENIICS/PARIS SUD
Master :

1. Introduction

X-ray fluorescence (XRF) is a powerful quantitative and qualitative analytical tool for elemental analysis; it is suitable for solid, liquid and powdered samples, and for a wide range of elements. It is non-destructive, requires little sample preparation and short measurement time.

In this work a standardless XRF setup with two measurement channels intended to actinide analysis is presented.

2. Miniature X-ray fluorescence system

The miniature XRF system includes two channels: the first one presents the classical XRF, the second channel contains additionally optical element located between the sample holder and the detector: the highly oriented pyrolytic graphite (HOPG) monochromator (Figure 1)




Figure 1. Monochromator based channel of the miniature XRF setup for spectrum analysis (left); comparison of measured spectra of the same sample measured with both channels (right).

HOPG can be used as a very efficient focusing and monochromatizing device [1, 2], allowing to focalize in a desired energy range (Figure 1), increase the intensity, and minimize undesirable spectrum parts.

It is possible to quantify the spectrum obtained from a sample with the classical XRF channel using fundamental parameters software [3]. The FP express the theoretical intensity/concentration relationship and requires the correct description of the setup. Since, the second channel has built-in optical element, which modifies the fluorescence intensity, it does not allow to quantify the spectrum using the FP algorithm. A solution consists in modeling of the transfer function of the monochromator (the function that represents the relationship between the input and output of the optical element) and include it in the FP algorithm.




Figure 2. Simulation results of the diffraction of x-rays by cylindrical HOPG monochromator with x-ray tracing (XRT) package: a polychromatic source spectrum implemented before the monochromator (left); multiple-reflection processes in HOPG cylinder (center); obtained spectrum after passing through the monochromator (right).

3. Simulation of the XRF system

The modelization of the optical element of the setup is performed with x-ray tracing (XRT) package [5]. The XRT allows to modelize only the multiple-reflection processes realized in cylindrical HOPG monochromator rather than all physical interactions in XRF setup. The mosaic structure of a presented HOPG crystal was successfully implemented in the code. Simulation results are illustrated in the Figure 2. In order to simulate the whole setup, it is necessary to obtain

the input source for the HOPG monochromator. This can be performed with the Monte Carlo (MC) simulation code of electron and photon transport [4]. Previously, it was verified that the simulated results of the classical XRF channel with the MC simulation code are in a good agreement with experimental results. The combination of both simulation code results permits to modelize the optical-based channel of the setup.

A good agreement between simulation results and experimental data enables to obtain a transfer function of monochromator and include it in the fundamental parameters algorithm, allowing to quantify the results obtained with the specific XRF system. Furthermore, using the simulation codes mentioned above, the mini XRF setup could be modified in order to improve the performance.

- [1] I. G. Grigorieva, A. A. Antonov, *Spectrom.*, 32, 64–68 (2003)
- [2] H. Legall, H. Stiel, V. Arkadiev, A. A. Bjeoumikhov, *Opt. Express*, 14, 4570–4576 (2006).
- [3] V. A. Solé, E. Papillon, M. Cotte, Ph. Walter, J. Susini, *Spectrochim. Acta Part B* 62, 63–68 (2007).
- [4] F. Salvat, et al., “PENELope-2014: A Code System for Monte Carlo Simulation of Electron and Photon Transport”, OECD NEA Data Bank/NSC DOC (2011).
- [5] K. Klementiev and R. Chernikov, *Proc. SPIE 9209, Advances in Computational Methods for X-Ray Optics III*, 92090A (2014).