

### Tungsten gross erosion and plasma impurity contamination in WEST phase I

L Colas, C Guillemaut, J P Gunn, R Guirlet, C Desgranges, P Devynck, N Fedorczak, J Hillairet, E A Unterberg, C C Klepper, et al.

### ► To cite this version:

L Colas, C Guillemaut, J P Gunn, R Guirlet, C Desgranges, et al.. Tungsten gross erosion and plasma impurity contamination in WEST phase I: A statistical comparison of LH and ICRF-heated L-mode plasmas. FEC2023 -29th IAEA Fusion Energy Conference, Oct 2023, Londres, United Kingdom. . cea-04353881

### HAL Id: cea-04353881 https://cea.hal.science/cea-04353881

Submitted on 19 Dec 2023  $\,$ 

**HAL** is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers. L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.



# **TUNGSTEN GROSS EROSION AND PLASMA IMPURITY CONTAMINATION IN WEST PHASE I** A statistical comparison of LH and ICRF-heated L-mode plasmas

L. COLAS, C. GUILLEMAUT, J.P. GUNN, R. GUIRLET, C. DESGRANGES, P. DEVYNCK, N. FEDORCZAK, J. HILLAIRET IRFM, CEA-Cadarache, 13108 Saint-Paul-lez-Durance, France Oak Ridge National Laboratory, Oak Ridge, Tennessee 37830, United States of America E.A. UNTERBERG, C.C. KLEPPER **G. URBANCZYK** Max-Planck-Institut für Plasmaphysik, Boltzmannstrasse 2, D-85748 Garching, Germany THE WEST TEAM http://west.cea.fr/WESTteam

## Goal:

- All-metal Magnetic Fusion devices prone to core contamination with high-Z impurities.
- This contribution documents experimentally the role of different categories of Plasma Facing Components (PFCs) in the core impurity contamination.

## **Experimental procedure:**

- Statistics over 2 experimental sessions at the end of WEST first operational phase.
- Change differently the W erosion on different PFC categories  $\rightarrow$  scan heating power

# **Divertor regimes**



- $P_{tot}$  over similar L-mode plasmas ( $B_t$ ,  $I_p$ ,  $\langle n_e \rangle$ ) with varying mix of LH and ICRF waves.
- Split data into 5 series  $\bullet = * \triangle$  depending on heating method and divertor state.
- Monitor gross W erosion using spectral lines W I ( $\lambda$ =400,9nm) & D I ( $\lambda$ =434,1nm) from visible spectroscopy on outboard LH and IC antenna limiters, as well as outer divertor.
- Look for correlation with core radiation properties and global plasma performance.

## Main findings:

- LH-only pulses are consistent with earlier scans of  $P_{tot} \rightarrow$  serve as reference pulses
- Compared to LH-only pulses at similar  $P_{tot}$ - $P_{rad}$ , enhanced gross W erosion on limiters of active IC antennas, correlated with RF voltage feeding local IC antenna.
- In presence of ICRH, reduced / suppressed W erosion near Outer Strike Point.
- 2 divertor regimes in IC-only discharges, associated with different radiation patterns.
- At first sight, P<sub>rad,bulk</sub>~45%P<sub>tot</sub> whatever the heating method. Closer look reveals ~25% extra core radiation & ~10% reduced energy content, when both ICRF-enhanced limiter W sources & divertor W sources are present. Compensation of opposite variations on limiter & divertor gross W sources ?

# **Gross W sources from antenna** limiters at the outer mid-plane



Visible spectro., averaged LH ant. lim. 26 & 27/01/2021



**ICRF** antenna limiters



10

0

15

 $V_{O2}$  [kV]

20

25

**Proxy: W I line brightness** ( $\lambda$ =400.9nm) averaged over all LOSs on LH limiters

- Caveat: no systematic SOL  $T_e$  profiles in main chamber  $\rightarrow$  single S/XB used over all database to convert brighness into particle fluxes.
- Some LH LOS magnetically connected to active IC antennas ?
- W I line brightness  $\uparrow$  with  $P_{tot}$ - $P_{rad}$
- Partly attributed to enhanced D I line brightness ( $\lambda$ =434.1nm), averaged over LOS  $\rightarrow$  proxy for particle flux onto limiters.
- Partly also to W I/D I ratio  $\rightarrow$  proxy for effective sputtering yield.
- W I line brightness  $vs P_{tot}$ - $P_{rad}$  is largely independent of heating method
- 2 regimes for D I line brightness ?

### **Ohmic & LH-only phases: similar** behaviour as LH grill limiters

- WI line brightness  $\uparrow$  with  $P_{tot}$ - $P_{rad}$
- Partly associated with larger DI line brightness
- Partly also with WI/DI ratio.
- At similar  $P_{tot}$ ,  $-P_{rad}$ , larger WI line brightness in the presence of ICRH
- **\* LH-only**
- Mainly associated with larger WI/DI

## **Core radiation, estimated core W** contamination & performance



- ratio.
- Several regimes for DI line brightness on top?
- **Proxy for enhancement factor: ratio.** of averaged W I line brightness  $(\lambda = 400.9 \text{nm})$  IC lim./LH grill lim.
  - Ratio close to 1 in ohmic & LH-only
  - pulses
- Up to ×3 in the presence of ICRH
- $\star \Delta \equiv$  compared to LH-only series  $\blacklozenge$ .
- Q2 ICRF antenna was always active in dipole phasing during reported ICRF pulses, sometimes with Q1.
- Correlated with RF voltage averaged over 4 feeding ports on antenna Q2
- Observation consistent with RF sheath rectification on active IC antennas.
- Factor 3 on 2 active IC antennas ⇔ number of ant. Limiters:  $10 \rightarrow 18 \rightarrow 10$ +80% gross W erosion on limiters.

## **Outlook for future WEST experiments:**

- Role of other PFCs (baffle, upper divertor) ?  $\rightarrow$  specific materials on these PFCs ?
- Better divertor coverage, poloidal asymmetries of  $P_{rad}$ ?  $\rightarrow$  vertical bolometric LOS
- Exploit other plasma scenarios: controlled divertor recycling, add ECRH to heating mix